

BC433-H
Performance Data

ALTERNATOR RPM	OUTPUT AMPS
2250	2.0
2500	6.8
2750	11.8
3000	14.9
3250	18.0
3500	20.4
4000	23.8
4500	26.5
5000	29.1
5500	29.4
6000	30.4
6500	31.1